

# EE372 - Electric Machinery and Power Systems Analysis

## Miscellaneous formulae

### Physics:

Work(W) =  $\int F dr = \int \tau d\theta$ , Power =  $\frac{dW}{dt}$

Flux density:  $B = \frac{\mu N i}{l_c}$  for  $i$  amperes in coil of  $N$  turns and mean flux path length  $l_c$

Total flux( $\phi$ ):  $\phi = \int \mathbf{B} \cdot d\mathbf{A}$

Faraday's and Lenz's laws for  $N$  turns around flux  $\phi$ :  $e_{ind} = -N \frac{d\phi}{dt}$

Force on wire carrying  $i$  amperes in field of flux density  $\mathbf{B}$ :  $\mathbf{F} = i(\mathbf{l} \times \mathbf{B})$

Voltage induced in conductor moving at velocity  $\mathbf{v}$  in flux density  $\mathbf{B}$ :  $e_{ind} = (\mathbf{v} \times \mathbf{B}) \cdot \mathbf{l}$

Torque between two flux fields  $\mathbf{B}_R$  and  $\mathbf{B}_S = k\mathbf{B}_R \times \mathbf{B}_S$ .

### General:

Complex power:  $\mathbf{S} = \mathbf{VI}^* = P + jQ$

Turns ratio of transformer:  $a = \frac{N_p}{N_s}$

Referencing of load impedance through transformer (ref. to primary):  $\mathbf{Z}'_L = a^2 \mathbf{Z}_L$

Per-unit analysis:  $Z_{base} = \frac{(V_{base})^2}{S_{base}} = \frac{V_{base}}{I_{base}}$ ,  $S_{base} = V_{base} I_{base}$ .

Transformer phasor diagrams (ref. to secondary):  $\frac{\mathbf{V}_P}{a} = \mathbf{V}_s + R_{eq} \mathbf{I}_S + jX_{eq} \mathbf{I}_S$

Per-unit in 3-phase:  $Z_{base} = \frac{3(V_{LN,base})^2}{S_{base}}$ ,  $I_{base} = \frac{S_{base}}{3V_{LN,base}}$

Voltage induced in coils of P-pole stator windings with  $N_C$  turns enclosing total flux  $\phi_{tot}$  in P-pole field, and rotating at speed  $\omega_m$  relative to magnetic field:  $N_C \phi_{tot} \omega_e \cos(\omega_e t)$ , where  $\omega_e = \omega_m P/2$ .

Mechanical power in rotating machine:  $P_{conv} = \tau_{ind} \omega_m$ .

Power output by rotating machine:  $P_{out} = \tau_{load} \omega_m$ .

"Regulation" of quantity  $\gamma$ :  $\frac{\gamma_{no\ load} - \gamma_{full\ load}}{\gamma_{full\ load}} \times 100\%$

### Motors:

Induction motor speed:  $n_{sync} = \frac{120 * f_e}{no.\ poles}$ ,  $s = \frac{n_{sync} - n_m}{n_{sync}}$

Induction rotor internal frequency:  $f_r = s f_e$ .

Power transferred to induction rotor:  $P_{AG} = P_{conv} + P_{RCL} = \tau_{ind} \omega_{sync}$

Three-phase induction motor torque:  $\tau_{ind} = \frac{3V_{TH}^2 R_2/s}{\omega_{sync} [(R_{TH} + R_2/s)^2 + (X_{TH} + X_2)^2]}$

DC motor converted power:  $P_{conv} = E_A I_A$

Back EMF in DC motor:  $E_A = K \phi \omega$ .

Induced Torque in DC motor:  $\tau_{ind} = K \phi I_A$

Shunt DC motor speed:  $\omega = \frac{V_t}{K \phi} - \frac{R_A}{(K \phi)^2} \tau_{ind}$

Series DC motor speed:  $\frac{V_T}{\sqrt{K c} \sqrt{\tau_{ind}}} - \frac{R_A + R_S}{K c}$